

微型交流减速电机

6RK 交流减速电机 (0.12~140W)(100mm)



微型
交流
减速
电机

电机特性表 Specifications of Motor

电机类型	电机型号	功率	频率	电压	电流	启动转矩	额定	额定转速	额定功率	额定电压	轴承	安装尺寸
可逆电机 Reversible motor	6RK120A-A	120	50	110	2.40	6500	3000	1300	35	230	6GU-K	6GM10X
	6RK120GU-A	120	60	110	2.20	7900	7550	1550	50	230	6GU-K	6GM10X
	6RK120A-C	120	50	220	1.10	7900	7550	1550	7	500	6GU-K	6GM10X
	6RK140A-A	140	50	110	2.80	11000	10500	1300	40	250	6GU-K	6GM10X
	6RK140GU-A	140	60	110	2.60	9300	8900	1550	30	250	6GU-K	6GM10X
	6RK140A-C	140	50	220	1.40	11000	10500	1300	10	500	6GU-K	6GM10X
	6RK140GU-C	140	60	220	1.30	9300	8900	1550	8	500	6GU-K	6GM10X
	6RK160A-A	160	50	110	3.20	15000	14500	1300	50	250	6GU-K	6GM10X
	6RK160GU-A	160	60	110	3.00	12600	12100	1550	40	250	6GU-K	6GM10X
	6RK160A-C	160	50	220	1.60	15000	14500	1300	15	500	6GU-K	6GM10X

外形尺寸 Outline Dimension

电机 Motor

安装尺寸图

带刹车

带减速机 Gearbox

40.5

型号 Model	减速比 Reduction Ratio	L1 (mm)	L2 (mm)	L3 (mm)	h (mm)
6RK120A-A, 6RK120GU-A	1:3~1:300	142	65	207	10
6RK140A-A, 6RK140GU-A	1:3~1:300	142	65	207	10

带减速机电机 Gear Motor



扭矩表 Torque Table

kg·m / N·m (牛·米)

同步转速 : r/min	500	300	200	150	120	100	75	60	50	30	20	15	10	7.5	6	5	3
--------------	-----	-----	-----	-----	-----	-----	----	----	----	----	----	----	----	-----	---	---	---